

DIE SELECTOR CHART

APPLICATION	CONDUCTOR		CONNECTOR				HYDRAULIC TOOLS							
							B15MD		HT45-E B450ND-BV		HT51 RH50 B500 B500ND B550			
							DIE SET	NEST	INDEN- TOR	DIE SET	NEST	INDEN- TOR	DIE SET	
COPPER CONDUCTORS	Conductor Size sqmm		TERMINAL		SPLICE	DIE SET	NEST	INDEN- TOR	DIE SET	NEST	INDEN- TOR	DIE SET		
	Low Str.	Flex												
	A.-M.	0,25 ÷ 2,5	A 03-M. A 06-M.			L 03-M / L 03-P L 06-M / L 06-P	ME03/2-15 MA03/3-15							
	A.-2M.	4 ÷ 6	A 1-M. A 1-L.			L 1-M L 1-P	ME03/2-15 MA03/3-15	MA1	PA1	ME1	MA1-50	PA1-50	ME1-50	
		10	A 2-M. A 2-L. A 2-P12 A 2-U.	A 2-2M.		L 2-M L 2-P	ME03/2-15 ME2/3-15 MA03/3-15			ME2			ME2-50	
	A.-L.	16	A 3-M. A 3-L. A 3-P14 A 3-P22R. A 3-U.	A 3-2M. 2A 3-M.		L 3-M L 3-P	ME2/3-15 MA03/3-15	MA2.3			MA2.3-50	PA5-50	ME3-50	
	A.-P.	25	A 5-M. A 5-L. A 5-P16 A 5-P22R.	A 5-2M. 2A 5-M.		L 5-M L 5-P		MA5		ME5	MA5-50		ME5-50	
	A.-PR.	35	25* 35	A 7-M. A 7-L. A 7-P20	A 7-2M. 2A 7-M.		L 7-M L 7-P		MA7		ME7	MA7-50	PA10-50	ME7-50
	A.-U.	50	35* 50	A 10-M. A 10-L. A 10-P25	A 10-2M. 2A 10-M. 2A10-2M.	L 10-M L 10-P		MA10		ME10	MA10-50		ME10-50	
		70	50* 70	A 14-M. A 14-L. A 14-P30	A 14-2M. 2A 14-M. 2A14-2M.	L 14-M L 14-P				ME14	MA14-50	PA19-50	ME14-50	
										ME17			ME17-50	
	2A.-M.	95	70* 95	A 19-M. A 19-L.	A 19-2M. 2A 19-M. 2A19-2M.	L 19-M L 19-P				ME19	MA19-50		ME19-50	
		120	95* 120	A 24-M. A 24-L.	A 24-2M. 2A 24-M. 2A24-2M.	L 24-M L 24-P				ME24	MA24-50	PA24-50	ME24-50	
	2A.-2M.	150	120* 150	A 30-M. A 30-L.	A 30-2M. 2A 30-M. 2A30-2M.	L 30-M L 30-P				ME30			ME30-50	
		185	150* 185	A 37-M. A 37-L. A 37-4ESI	A 37-2M. 2A 37-M. 2A37-2M.	L 37-M L 37-P							ME37-50	
		240	185* 240	A 48-M. A 48-L. A 48-4ESI	A 48-2M. 2A 48-M. 2A48-2M.	L 48-M L 48-P							ME48-50	
	L.-M.	300	240 300	A 60-M. A 60-L. A 60-4ESI	A 60-2M. 2A 60-M. 2A60-2M.	L 60-M L 60-P							ME60-50**	
	L.-P.	400	300 400	A 80-M. A 80-4ESI	A 80-2M. 2A 80-M. 2A80-2M.	L 80-M								
		500	400 500	A 100-M. A 100-4ESI	A 100-2M. 2A 100-M. 2A100-2M.	L 100-M								
		630	500 630	A 120-M. A 120-4ESI	A 120-2M. 2A 120-M. 2A120-2M.	L 120-M								
	800	630	A 160-M. A 160-4ESI	A 160-2M. 2A 160-M. 2A160-2M.	L 160-M									
A.-4ESI	1000	800	A 200-M.	2A 200-M. 2A200-2M.	L 200-M									
EXTRA FLEXIBLE COPPER CONDUCTORS		35	A 9-M.					MA9	PA10	ME9	MA9-50	PA10-50	ME9-50	
	A.-M.	50	A 12-M.							ME12	MA12-50	PA19-50	ME12-50	
		70	A 17-M.							ME17	MA17-50		ME17-50	
		95	A 20-M.							ME20	MA20-50		ME20-50	
		120	A 29-M.							ME29			ME29-50	
		150	A 35-M.										ME35-50	
		185	A 40-M.										ME40-50	

= Hexagonal crimp (use one size up with fine stranded conductors, E.G.: 95* fine stranded use A19.-. + ME 19 or A 20.-. + ME 20)

= Indent crimp

* Contact Cembre for appropriate die set