






# DIE SELECTOR CHART

APPLICATION	CONDUCTOR	CONNECTOR		B15MD DIE SET	HT45-E B450ND-BV DIE SET	HT51 RH50 B500 B500ND B550 DIE SET		HT120 and tools and heads with 130 kN crimping force		ECW-H3D		RHU520
		LUGS	SPICES			HT51 RH50 B500 B500ND B550 DIE SET	HT120 and tools and heads with 130 kN crimping force	NEST	INDENTOR	NEST	INDENTOR	
 AL DIN 46234	6-10	Q10..				MQ10-50	MQ10-C	MQ10-C				Adaptor AU520-130C with die set MQ...
	10-16	Q16..				MQ16-50	MQ16-C	MQ16-C				
	16-25	Q25..				MQ25-50	MQ25-C	MQ25-C				
	25-35	Q35..				MQ35-50	MQ35-C	MQ35-C				
	35-50	Q50..				MQ50-50	MQ50-C	MQ50-C				
	50-70	Q70..				MQ70-50	MQ70-C	MQ70-C				
	70-95	Q95..										
	95-120	Q120..										
	120-150	Q150..										
	150-185	Q185..										
 AL DIN 46235 - 46267 T.1	185-240	Q240..										Adaptor AU230-130D with die set MQ...
	6	DR6..	DSV6	MK5		MK5-50	MK5-C	MK5-C				
	10	DR10..	DSV10	MK5/8-15		MK6-50	MK6-C	MK6-C				
	16	DR16..	DSV16	MK8		MK8-50	MK8-C	MK8-C				
	25	DR25..	DSV25	MK10		MK10-50	MK10-C	MK10-C				
	35	DR35..	DSV35	MK12		MK12-50	MK12-C	MK12-C				
	50	DR50..	DSV50	MK14		MK14-50	MK14-C	MK14-C				
	70	DR70..	DSV70	MK16		MK16-50	MK16-C	MK16-C				
	95	DR95..	DSV95	MK18		MK18-50	MK18-C	MK18-C				
	120	DR120..	DSV120	MK20		MK20-50	MK20-C	MK20-C				
 AL DIN 46235 - 46267 T.1	150	DR150..	DSV150	MK22L		MK22-50	MK22-C	MK22-C				Adaptor AU520-130C with die set MK...-C
	185	DR185..	DSV185			MK25-50	MK25-C	MK25-C				
	240	DR240..	DSV240			MK28-50	MK28-C	MK28-C				
	300	DR300..	DSV300			MK32-50*	MK32-C	MK32-C				
	400	DR400..	DSV400									
	500	DR500..	DSV500									
	625	DR625..	DSV625									
	800	DR800..	DSV800									
	1000	DR1000..	DSV1000									
	 COPPER CONDUCTORS	10	HR10..	HSV10	MH10		MH10-50	MH10-C	MH10-C			
16		HR16..	HSV16	MH16		MH16-50	MH16-C	MH16-C				
25		HR25..	HSV25	MH25		MH25-50	MH25-C	MH25-C				
35		HR35..	HSV35	MH35		MH35-50	MH35-C	MH35-C				
50		HR50..	HSV50	MH50		MH50-50	MH50-C	MH50-C				
70		HR70..	HSV70	MH70		MH70-50	MH70-C	MH70-C				
95		HR95..	HSV95	MH95		MH95-50	MH95-C	MH95-C				
120		HR120..	HSV120	MH120		MH120-50	MH120-C	MH120-C				
150		HR150..	HSV150	MH150		MH150-50	MH150-C	MH150-C				
185		HR185..	HSV185			MH185-50	MH185-C	MH185-C				
 COPPER CONDUCTORS	240	HR240..	HSV240			MH240-50	MH240-C	MH240-C				
	300	HR300..	HSV300			MH300-50*	MH300-C	MH300-C				
	400						MH400-C	MH400-C				
	500											
	630											

◊ Tools type HT 81-U and RHU 81 with adaptor type 6780232 can use the same dies of HT 51 but are equipped with spring type 6522051  
 ◊ The tools type HT 61, RH 61 and B600 use the same dies as the HT 51 with a spring type 6522051.

NB: for through connectors this is the number of crimps per conductor  
 \* Only for B500, B500ND and RH50

